

ES1AL THRU ES1JL


Single Phase 1.0AMP Surface Mount Super Fast Recovery Rectifier

Features

- · Glass passivated device
- · Ideal for surface mouted applications
- · Low reverse leakage
- · Metallurgically bonded construction
- High temperature soldering guaranteed: 260 °C /10 seconds,0.375"(9.5mm) lead length, 5 lbs. (2.3kg) tension
- Plastic material-UL flammability 94V-0

Mechanical Data

- · Case: SOD-123FL, molded plastic
- Terminals: plated leads solderable per MIL-STD-750, Method 2026
- · Polarity: Color band denotes cathode end
- · Mounting position: Any



Dimensions in inches and (millimeters)

Maximum Ratings and Electrical Characteristics

Rating at 25℃ ambient temperature unless otherwise specified.

Single Phase, half wave, 60Hz, resistive or inductive load.

For capacitive load, derate current by 20%.

TYPE NUMBER	SYMBOL	ES1AL	ES1BL	ES1DL	ES1GL	ES1JL	UNITS
	Code	EA	EB	ED	EG	EJ	
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	VRRM	50	100	200	400	600	V
	VRWM						
	VDC						
RMS Reverse Voltage	VRMS	35	70	140	280	420	V
Average Rectified Output Current	I F(AV)	1.0					Α
Non-Repetitive Peak Forward Surge @T _{j=25} ℃		30 24					А
Current 8.3ms Single half sine-wave@T _{j=125} °C	IFSM						
Superimposed On Rated Load (JEDEC Method)							
Non-Repetitive Peak Forward Surge @T _{j=25} ℃		60					
Current 1.0ms Single half sine-wave @Tj=125°C	IFSM 48						Α
Superimposed On Rated Load (JEDEC Method)							
10000 times of the wave surge current	Iгsм	22.5					Α
(time width 1ms, time interval 3s)	II OW	-22.0					
I ² t Rating for Fusing (t < 8.3ms)	l²t	3.735					A ² s
Forward Voltage per element @IF=1.0A	VFM	0.95 1.3 1.7			1.7	V	
Peak Reverse Current @TA =25℃ At Rated DC Blocking Voltage @TA =125℃	lr	5.0 100					
							uA
Maximum reverse recovery time @T _A =25°C	Т	35					ns
(Note 1) @TA =125 ℃	Trr	200					
Typical Junction Capacitance (Note 2)	CJ	10					pF
Typical thermal resistance	Reja	60					°C/W
Operating and Storage Temperature Range	Т _J ,Тsтg	-55to+150					$^{\circ}\!\mathbb{C}$
	-	•					

Note:1.Measured with IF=0.5A, IR=1A, Irr=0.25A.

2 Measured at 1.0 MHz and Applied reverse Voltage of 4.0V D.C.

version:04 1 of 3



ES1AL THRU ES1JL

Single Phase 1.0AMP Surface Mount Super Fast Recovery Rectifier

Instantaneous Reverse Current (uA)

20

Fig. 1 Typical Forward Current Derating Curve




Fig. 3 Max Non-Repetitive Peak Fwd Surge Current




Fig.5 Typical Capacitance






Fig. 2 Typical Instantaneous Forward Characteristics



V_F, Instantaneous Forward Voltage (V)

Fig.4 Typical Reverse Chracteristics



Percent Of Rated Peak Reverse Voltage (%)

version:04 2 of 3



ES1AL THRU ES1JL

Single Phase 1.0AMP Surface Mount Super Fast Recovery Rectifier

Important Notice and Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from XINNUO
- XINNUO reserves the right to make changes to this document and its products and specifications
- XINNUO disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- XINNUO does not assume any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the here in document are examples of standard use and operation. Customers are responsible in comprehending the suitable use in particular applications.
 - XINNUO makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown here in are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own ris k andagree to fully indemnify XINNUO for any damages resulting from such improper use or sale.
- Since XINNUO uses lot number as the tracking base, please provide the lot number for tracking when complaining.

version:04 3 of 3